

# Math 221: LINEAR ALGEBRA

## Chapter 1. Systems of Linear Equations

### §1-2. Gaussian Elimination

Le Chen<sup>1</sup>

Emory University, 2020 Fall

(last updated on 10/26/2020)



Creative Commons License  
(CC BY-NC-SA)

<sup>1</sup>Slides are adapted from those by Karen Seyffarth from University of Calgary.

Row-Echelon Form

Solving Systems of Linear Equations – Gaussian Elimination

Rank

Uniqueness of the Reduced Row-Echelon Form

One Application



# Row-Echelon Matrix

## Definition

A matrix is called a **row-echelon matrix** if

- ▶ All rows consisting entirely of zeros are at the bottom.
- ▶ The first nonzero entry in each nonzero row is a 1 (called the leading 1 for that row).
- ▶ Each leading 1 is to the right of all leading 1's in rows above it.

A matrix is said to be in the **row-echelon form (REF)** if it a row-echelon matrix.

## Example

$$\begin{bmatrix} 0 & 1 & * & * & * & * & * & * \\ 0 & 0 & 0 & 1 & * & * & * & * \\ 0 & 0 & 0 & 0 & 1 & * & * & * \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 1 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \end{bmatrix}$$

where \* can be any number.

## Definition

A matrix is called a **reduced row-echelon matrix** if

- ▶ Row-echelon matrix.
- ▶ Each leading 1 is the only nonzero entry in its column.

A matrix is said to be in the **reduced row-echelon form (RREF)** if it a reduced row-echelon matrix.

## Definition

A matrix is called a **reduced row-echelon matrix** if

- ▶ Row-echelon matrix.
- ▶ Each leading 1 is the only nonzero entry in its column.

A matrix is said to be in the **reduced row-echelon form (RREF)** if it a reduced row-echelon matrix.

## Example

$$\begin{bmatrix} 0 & 1 & * & 0 & 0 & * & * & 0 \\ 0 & 0 & 0 & 1 & 0 & * & * & 0 \\ 0 & 0 & 0 & 0 & 1 & * & * & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 1 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \end{bmatrix}$$

where \* can be any number.

## Examples

Which of the following matrices are in the REF?

Which ones are in the RREF?

## Examples

Which of the following matrices are in the REF?

Which ones are in the RREF?

$$(a) \begin{bmatrix} 0 & 1 & 2 & 0 \\ 0 & 0 & 1 & 2 \end{bmatrix}$$

$$(b) \begin{bmatrix} 1 & 0 & 2 & 0 \\ 0 & 0 & 1 & 2 \end{bmatrix}$$

$$(c) \begin{bmatrix} 1 & 0 & 2 & 0 \\ 0 & 0 & 1 & 2 \\ 0 & 0 & 1 & 2 \end{bmatrix}$$

$$(d) \begin{bmatrix} 1 & 0 & 2 & 0 \\ 0 & 1 & 1 & 2 \end{bmatrix}$$

$$(e) \begin{bmatrix} 1 & 2 & 0 & 0 \\ 0 & 0 & 1 & 2 \end{bmatrix}$$

$$(f) \begin{bmatrix} 1 & 2 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \end{bmatrix}$$



## Example

Suppose that the following matrix is the augmented matrix of a system of linear equations. We see from this matrix that the system of linear equations has four equations and seven variables.

$$\begin{array}{ccccccc} x_1 & x_2 & x_3 & x_4 & x_5 & x_6 & x_7 \\ \left[ \begin{array}{ccccccc|c} 1 & -3 & 4 & -2 & 5 & -7 & 0 & 4 \\ 0 & 0 & 1 & 8 & 0 & 3 & -7 & 0 \\ 0 & 0 & 0 & 1 & 1 & -1 & 0 & -1 \\ 0 & 0 & 0 & 0 & 0 & 0 & 1 & 2 \end{array} \right] \end{array}$$

Note that the matrix is a **row-echelon matrix**.

## Example

Suppose that the following matrix is the augmented matrix of a system of linear equations. We see from this matrix that the system of linear equations has four equations and seven variables.

$$\begin{array}{ccccccc|c} x_1 & x_2 & x_3 & x_4 & x_5 & x_6 & x_7 & \\ \hline 1 & -3 & 4 & -2 & 5 & -7 & 0 & 4 \\ 0 & 0 & 1 & 8 & 0 & 3 & -7 & 0 \\ 0 & 0 & 0 & 1 & 1 & -1 & 0 & -1 \\ 0 & 0 & 0 & 0 & 0 & 0 & 1 & 2 \end{array}$$

Note that the matrix is a **row-echelon matrix**.

- Each column of the matrix corresponds to a variable, and the **leading variables** are the variables that correspond to columns containing leading ones.

## Example

Suppose that the following matrix is the augmented matrix of a system of linear equations. We see from this matrix that the system of linear equations has four equations and seven variables.

$$\begin{array}{ccccccc|c} x_1 & x_2 & x_3 & x_4 & x_5 & x_6 & x_7 & \\ \hline 1 & -3 & 4 & -2 & 5 & -7 & 0 & 4 \\ 0 & 0 & 1 & 8 & 0 & 3 & -7 & 0 \\ 0 & 0 & 0 & 1 & 1 & -1 & 0 & -1 \\ 0 & 0 & 0 & 0 & 0 & 0 & 1 & 2 \end{array}$$

Note that the matrix is a **row-echelon matrix**.

- ▶ Each column of the matrix corresponds to a variable, and the **leading variables** are the variables that correspond to columns containing leading ones.
- ▶ The remaining variables are called **non-leading variables**.

## Example

Suppose that the following matrix is the augmented matrix of a system of linear equations. We see from this matrix that the system of linear equations has four equations and seven variables.

$$\begin{array}{ccccccc|c} x_1 & x_2 & x_3 & x_4 & x_5 & x_6 & x_7 & \\ \hline 1 & -3 & 4 & -2 & 5 & -7 & 0 & 4 \\ 0 & 0 & 1 & 8 & 0 & 3 & -7 & 0 \\ 0 & 0 & 0 & 1 & 1 & -1 & 0 & -1 \\ 0 & 0 & 0 & 0 & 0 & 0 & 1 & 2 \end{array}$$

Note that the matrix is a **row-echelon matrix**.

- ▶ Each column of the matrix corresponds to a variable, and the **leading variables** are the variables that correspond to columns containing leading ones.
- ▶ The remaining variables are called **non-leading variables**.

We will use elementary row operations to transform a matrix to row-echelon (REF) or reduced row-echelon form (RREF).



# Solving Systems of Linear Equations – Gaussian Elimination

## Theorem

Every matrix can be brought to (reduced) row-echelon form by a sequence of elementary row operations.

# Solving Systems of Linear Equations – Gaussian Elimination

## Theorem

Every matrix can be brought to (reduced) row-echelon form by a sequence of elementary row operations.

## Gaussian Elimination

To solve a system of linear equations proceed as follows:

1. Carry the augmented matrix to a reduced row-echelon matrix using elementary row operations.

# Solving Systems of Linear Equations – Gaussian Elimination

## Theorem

Every matrix can be brought to (reduced) row-echelon form by a sequence of elementary row operations.

## Gaussian Elimination

To solve a system of linear equations proceed as follows:

1. Carry the augmented matrix to a reduced row-echelon matrix using elementary row operations.
2. If a row of the form  $[0 \ 0 \ \cdots 0 \mid 1]$  occurs, the system is inconsistent.



# Solving Systems of Linear Equations – Gaussian Elimination

## Theorem

Every matrix can be brought to (reduced) row-echelon form by a sequence of elementary row operations.

## Gaussian Elimination

To solve a system of linear equations proceed as follows:

1. Carry the augmented matrix to a reduced row-echelon matrix using elementary row operations.
2. If a row of the form  $[0 \ 0 \ \cdots \ 0 \mid 1]$  occurs, the system is inconsistent.
3. Otherwise assign the nonleading variables (if any) **parameters** and use the equations corresponding to the reduced row-echelon matrix to solve for the leading variables in terms of the parameters.

## Problem

Solve the system

$$\begin{cases} 2x + y + 3z = 1 \\ 2y - z + x = 0 \\ 9z + x - 4y = 2 \end{cases}$$

### Problem

Solve the system

$$\begin{cases} 2x + y + 3z = 1 \\ 2y - z + x = 0 \\ 9z + x - 4y = 2 \end{cases}$$

### Solution

$$\left[ \begin{array}{ccc|c} 2 & 1 & 3 & 1 \\ 1 & 2 & -1 & 0 \\ 1 & -4 & 9 & 2 \end{array} \right]$$

### Problem

Solve the system

$$\begin{cases} 2x + y + 3z = 1 \\ 2y - z + x = 0 \\ 9z + x - 4y = 2 \end{cases}$$

### Solution

$$\left[ \begin{array}{ccc|c} 2 & 1 & 3 & 1 \\ 1 & 2 & -1 & 0 \\ 1 & -4 & 9 & 2 \end{array} \right] \xrightarrow{r_1 \leftrightarrow r_2} \left[ \begin{array}{ccc|c} 1 & 2 & -1 & 0 \\ 2 & 1 & 3 & 1 \\ 1 & -4 & 9 & 2 \end{array} \right]$$

### Problem

Solve the system

$$\begin{cases} 2x + y + 3z = 1 \\ 2y - z + x = 0 \\ 9z + x - 4y = 2 \end{cases}$$

### Solution

$$\left[ \begin{array}{ccc|c} 2 & 1 & 3 & 1 \\ 1 & 2 & -1 & 0 \\ 1 & -4 & 9 & 2 \end{array} \right]$$

$\rightarrow r_1 \leftrightarrow r_2$

$$\left[ \begin{array}{ccc|c} 1 & 2 & -1 & 0 \\ 2 & 1 & 3 & 1 \\ 1 & -4 & 9 & 2 \end{array} \right]$$

$\rightarrow -2r_1 + r_2, -r_1 + r_3$

$$\left[ \begin{array}{ccc|c} 1 & 2 & -1 & 0 \\ 0 & -3 & 5 & 1 \\ 0 & -6 & 10 & 2 \end{array} \right]$$

## Problem

Solve the system

$$\begin{cases} 2x + y + 3z = 1 \\ 2y - z + x = 0 \\ 9z + x - 4y = 2 \end{cases}$$

## Solution

$$\left[ \begin{array}{ccc|c} 2 & 1 & 3 & 1 \\ 1 & 2 & -1 & 0 \\ 1 & -4 & 9 & 2 \end{array} \right]$$

$\rightarrow r_1 \leftrightarrow r_2$

$$\left[ \begin{array}{ccc|c} 1 & 2 & -1 & 0 \\ 2 & 1 & 3 & 1 \\ 1 & -4 & 9 & 2 \end{array} \right]$$

$\rightarrow -2r_1 + r_2, -r_1 + r_3$

$$\left[ \begin{array}{ccc|c} 1 & 2 & -1 & 0 \\ 0 & -3 & 5 & 1 \\ 0 & -6 & 10 & 2 \end{array} \right]$$

$\rightarrow -2r_2 + r_3$

$$\left[ \begin{array}{ccc|c} 1 & 2 & -1 & 0 \\ 0 & -3 & 5 & 1 \\ 0 & 0 & 0 & 0 \end{array} \right]$$

## Problem

Solve the system

$$\begin{cases} 2x + y + 3z = 1 \\ 2y - z + x = 0 \\ 9z + x - 4y = 2 \end{cases}$$

## Solution

$$\left[ \begin{array}{ccc|c} 2 & 1 & 3 & 1 \\ 1 & 2 & -1 & 0 \\ 1 & -4 & 9 & 2 \end{array} \right]$$

$\rightarrow r_1 \leftrightarrow r_2$

$$\left[ \begin{array}{ccc|c} 1 & 2 & -1 & 0 \\ 2 & 1 & 3 & 1 \\ 1 & -4 & 9 & 2 \end{array} \right]$$

$\rightarrow -2r_1 + r_2, -r_1 + r_3$

$$\left[ \begin{array}{ccc|c} 1 & 2 & -1 & 0 \\ 0 & -3 & 5 & 1 \\ 0 & -6 & 10 & 2 \end{array} \right]$$

$\rightarrow -2r_2 + r_3$

$$\left[ \begin{array}{ccc|c} 1 & 2 & -1 & 0 \\ 0 & -3 & 5 & 1 \\ 0 & 0 & 0 & 0 \end{array} \right]$$

$\rightarrow -\frac{1}{3}r_2$

$$\left[ \begin{array}{ccc|c} 1 & 2 & -1 & 0 \\ 0 & 1 & -5/3 & -1/3 \\ 0 & 0 & 0 & 0 \end{array} \right]$$

## Problem

Solve the system

$$\begin{cases} 2x + y + 3z = 1 \\ 2y - z + x = 0 \\ 9z + x - 4y = 2 \end{cases}$$

## Solution

$$\left[ \begin{array}{ccc|c} 2 & 1 & 3 & 1 \\ 1 & 2 & -1 & 0 \\ 1 & -4 & 9 & 2 \end{array} \right] \xrightarrow{r_1 \leftrightarrow r_2} \left[ \begin{array}{ccc|c} 1 & 2 & -1 & 0 \\ 2 & 1 & 3 & 1 \\ 1 & -4 & 9 & 2 \end{array} \right]$$

$$\xrightarrow{-2r_1+r_2, -r_1+r_3} \left[ \begin{array}{ccc|c} 1 & 2 & -1 & 0 \\ 0 & -3 & 5 & 1 \\ 0 & -6 & 10 & 2 \end{array} \right] \xrightarrow{-2r_2+r_3} \left[ \begin{array}{ccc|c} 1 & 2 & -1 & 0 \\ 0 & -3 & 5 & 1 \\ 0 & 0 & 0 & 0 \end{array} \right]$$

$$\xrightarrow{-\frac{1}{3}r_2} \left[ \begin{array}{ccc|c} 1 & 2 & -1 & 0 \\ 0 & 1 & -5/3 & -1/3 \\ 0 & 0 & 0 & 0 \end{array} \right] \xrightarrow{-2r_2+r_1} \left[ \begin{array}{ccc|c} 1 & 0 & 7/3 & 2/3 \\ 0 & 1 & -5/3 & -1/3 \\ 0 & 0 & 0 & 0 \end{array} \right]$$



## Solution (continued)

Given the reduced row-echelon matrix

$$\left[ \begin{array}{ccc|c} 1 & 0 & 7/3 & 2/3 \\ 0 & 1 & -5/3 & -1/3 \\ 0 & 0 & 0 & 0 \end{array} \right]$$

x and y are **leading variables**; z is a **non-leading variable** and so assign a **parameter** to z.

## Solution (continued)

Given the reduced row-echelon matrix

$$\left[ \begin{array}{ccc|c} 1 & 0 & 7/3 & 2/3 \\ 0 & 1 & -5/3 & -1/3 \\ 0 & 0 & 0 & 0 \end{array} \right]$$

$x$  and  $y$  are **leading variables**;  $z$  is a **non-leading variable** and so assign a **parameter** to  $z$ . Thus the solution to the original system is given by

$$\left. \begin{array}{rcl} x & = & \frac{2}{3} - \frac{7}{3}s \\ y & = & -\frac{1}{3} + \frac{5}{3}s \\ z & = & s \end{array} \right\} \text{ for all } s \in \mathbb{R}.$$

## Problem

Solve the system

$$\begin{cases} x + y + 2z = -1 \\ y + 2x + 3z = 0 \\ z - 2y = 2 \end{cases}$$

### Problem

Solve the system 
$$\begin{cases} x + y + 2z = -1 \\ y + 2x + 3z = 0 \\ z - 2y = 2 \end{cases}$$

### Solution

$$\left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 2 & 1 & 3 & 0 \\ 0 & -2 & 1 & 2 \end{array} \right] \rightarrow^{-2r_1+r_2}$$

### Problem

Solve the system 
$$\begin{cases} x + y + 2z = -1 \\ y + 2x + 3z = 0 \\ z - 2y = 2 \end{cases}$$

### Solution

$$\left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 2 & 1 & 3 & 0 \\ 0 & -2 & 1 & 2 \end{array} \right] \xrightarrow{-2r_1 + r_2} \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 0 & -1 & -1 & 2 \\ 0 & -2 & 1 & 2 \end{array} \right]$$

$$\xrightarrow{-1 \cdot r_2}$$

### Problem

Solve the system 
$$\begin{cases} x + y + 2z = -1 \\ y + 2x + 3z = 0 \\ z - 2y = 2 \end{cases}$$

### Solution

$$\begin{aligned} & \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 2 & 1 & 3 & 0 \\ 0 & -2 & 1 & 2 \end{array} \right] \xrightarrow{-2r_1+r_2} \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 0 & -1 & -1 & 2 \\ 0 & -2 & 1 & 2 \end{array} \right] \\ & \xrightarrow{-1 \cdot r_2} \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 0 & 1 & 1 & -2 \\ 0 & -2 & 1 & 2 \end{array} \right] \end{aligned}$$

## Problem

Solve the system 
$$\begin{cases} x + y + 2z = -1 \\ y + 2x + 3z = 0 \\ z - 2y = 2 \end{cases}$$

## Solution

$$\begin{aligned} & \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 2 & 1 & 3 & 0 \\ 0 & -2 & 1 & 2 \end{array} \right] \xrightarrow{-2r_1 + r_2} \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 0 & -1 & -1 & 2 \\ 0 & -2 & 1 & 2 \end{array} \right] \\ & \xrightarrow{-1 \cdot r_2} \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 0 & 1 & 1 & -2 \\ 0 & -2 & 1 & 2 \end{array} \right] \xrightarrow{2r_2 + r_3} \left[ \begin{array}{ccc|c} 1 & 0 & 1 & 1 \\ 0 & 1 & 1 & -2 \\ 0 & 0 & 3 & -2 \end{array} \right] \\ & \xrightarrow{\frac{1}{3}r_3} \end{aligned}$$

## Problem

Solve the system

$$\begin{cases} x + y + 2z = -1 \\ y + 2x + 3z = 0 \\ z - 2y = 2 \end{cases}$$

## Solution

$$\begin{aligned} & \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 2 & 1 & 3 & 0 \\ 0 & -2 & 1 & 2 \end{array} \right] \xrightarrow{-2r_1+r_2} \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 0 & -1 & -1 & 2 \\ 0 & -2 & 1 & 2 \end{array} \right] \\ & \xrightarrow{-1 \cdot r_2} \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 0 & 1 & 1 & -2 \\ 0 & -2 & 1 & 2 \end{array} \right] \xrightarrow{2r_2+r_3} \left[ \begin{array}{ccc|c} 1 & 0 & 1 & 1 \\ 0 & 1 & 1 & -2 \\ 0 & 0 & 3 & -2 \end{array} \right] \\ & \xrightarrow{\frac{1}{3}r_3} \left[ \begin{array}{ccc|c} 1 & 0 & 1 & 1 \\ 0 & 1 & 1 & -2 \\ 0 & 0 & 1 & -2/3 \end{array} \right] \xrightarrow{-r_3+r_2, -r_3+r_1} \end{aligned}$$



## Problem

Solve the system 
$$\begin{cases} x + y + 2z = -1 \\ y + 2x + 3z = 0 \\ z - 2y = 2 \end{cases}$$

## Solution

$$\begin{aligned} & \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 2 & 1 & 3 & 0 \\ 0 & -2 & 1 & 2 \end{array} \right] \xrightarrow{-2r_1+r_2} \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 0 & -1 & -1 & 2 \\ 0 & -2 & 1 & 2 \end{array} \right] \\ & \xrightarrow{-1 \cdot r_2} \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 0 & 1 & 1 & -2 \\ 0 & -2 & 1 & 2 \end{array} \right] \xrightarrow{2r_2+r_3} \left[ \begin{array}{ccc|c} 1 & 0 & 1 & 1 \\ 0 & 1 & 1 & -2 \\ 0 & 0 & 3 & -2 \end{array} \right] \\ & \xrightarrow{\frac{1}{3}r_3} \left[ \begin{array}{ccc|c} 1 & 0 & 1 & 1 \\ 0 & 1 & 1 & -2 \\ 0 & 0 & 1 & -2/3 \end{array} \right] \xrightarrow{-r_3+r_2, -r_3+r_1} \left[ \begin{array}{ccc|c} 1 & 0 & 0 & 5/3 \\ 0 & 1 & 0 & -4/3 \\ 0 & 0 & 1 & -2/3 \end{array} \right] \end{aligned}$$

## Problem

Solve the system 
$$\begin{cases} x + y + 2z = -1 \\ y + 2x + 3z = 0 \\ z - 2y = 2 \end{cases}$$

## Solution

$$\begin{aligned} & \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 2 & 1 & 3 & 0 \\ 0 & -2 & 1 & 2 \end{array} \right] \xrightarrow{-2r_1+r_2} \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 0 & -1 & -1 & 2 \\ 0 & -2 & 1 & 2 \end{array} \right] \\ & \xrightarrow{-1 \cdot r_2} \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 0 & 1 & 1 & -2 \\ 0 & -2 & 1 & 2 \end{array} \right] \xrightarrow{2r_2+r_3} \left[ \begin{array}{ccc|c} 1 & 0 & 1 & 1 \\ 0 & 1 & 1 & -2 \\ 0 & 0 & 3 & -2 \end{array} \right] \\ & \xrightarrow{\frac{1}{3}r_3} \left[ \begin{array}{ccc|c} 1 & 0 & 1 & 1 \\ 0 & 1 & 1 & -2 \\ 0 & 0 & 1 & -2/3 \end{array} \right] \xrightarrow{-r_3+r_2, -r_3+r_1} \left[ \begin{array}{ccc|c} 1 & 0 & 0 & 5/3 \\ 0 & 1 & 0 & -4/3 \\ 0 & 0 & 1 & -2/3 \end{array} \right] \end{aligned}$$

The **unique** solution is  $x = 5/3$ ,  $y = -4/3$ ,  $z = -2/3$ .

### Problem

Solve the system 
$$\begin{cases} x + y + 2z = -1 \\ y + 2x + 3z = 0 \\ z - 2y = 2 \end{cases}$$

### Solution

$$\begin{aligned} & \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 2 & 1 & 3 & 0 \\ 0 & -2 & 1 & 2 \end{array} \right] \xrightarrow{-2r_1+r_2} \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 0 & -1 & -1 & 2 \\ 0 & -2 & 1 & 2 \end{array} \right] \\ & \xrightarrow{-1 \cdot r_2} \left[ \begin{array}{ccc|c} 1 & 1 & 2 & -1 \\ 0 & 1 & 1 & -2 \\ 0 & -2 & 1 & 2 \end{array} \right] \xrightarrow{2r_2+r_3} \left[ \begin{array}{ccc|c} 1 & 0 & 1 & 1 \\ 0 & 1 & 1 & -2 \\ 0 & 0 & 3 & -2 \end{array} \right] \\ & \xrightarrow{\frac{1}{3}r_3} \left[ \begin{array}{ccc|c} 1 & 0 & 1 & 1 \\ 0 & 1 & 1 & -2 \\ 0 & 0 & 1 & -2/3 \end{array} \right] \xrightarrow{-r_3+r_2, -r_3+r_1} \left[ \begin{array}{ccc|c} 1 & 0 & 0 & 5/3 \\ 0 & 1 & 0 & -4/3 \\ 0 & 0 & 1 & -2/3 \end{array} \right] \end{aligned}$$

The **unique** solution is  $x = 5/3$ ,  $y = -4/3$ ,  $z = -2/3$ .

Check your answer!

### Problem

Solve the system

$$\left\{ \begin{array}{rclclcl} -3x_1 & - & 9x_2 & + & x_3 & = & -9 \\ 2x_1 & + & 6x_2 & - & x_3 & = & 6 \\ x_1 & + & 3x_2 & - & x_3 & = & 2 \end{array} \right.$$

### Problem

Solve the system 
$$\begin{cases} -3x_1 & - & 9x_2 & + & x_3 & = & -9 \\ 2x_1 & + & 6x_2 & - & x_3 & = & 6 \\ x_1 & + & 3x_2 & - & x_3 & = & 2 \end{cases}$$

### Solution

$$\left[ \begin{array}{ccc|c} 1 & 3 & -1 & 2 \\ 2 & 6 & -1 & 6 \\ -3 & -9 & 1 & -9 \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 3 & -1 & 2 \\ 0 & 0 & 1 & 2 \\ 0 & 0 & -2 & -3 \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 3 & 0 & 4 \\ 0 & 0 & 1 & 2 \\ 0 & 0 & 0 & 1 \end{array} \right]$$

### Problem

Solve the system 
$$\begin{cases} -3x_1 & - & 9x_2 & + & x_3 & = & -9 \\ 2x_1 & + & 6x_2 & - & x_3 & = & 6 \\ x_1 & + & 3x_2 & - & x_3 & = & 2 \end{cases}$$

### Solution

$$\left[ \begin{array}{ccc|c} 1 & 3 & -1 & 2 \\ 2 & 6 & -1 & 6 \\ -3 & -9 & 1 & -9 \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 3 & -1 & 2 \\ 0 & 0 & 1 & 2 \\ 0 & 0 & -2 & -3 \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 3 & 0 & 4 \\ 0 & 0 & 1 & 2 \\ 0 & 0 & 0 & 1 \end{array} \right]$$

The last row of the final matrix corresponds to the equation

$$0x_1 + 0x_2 + 0x_3 = 1$$

which is impossible!

Therefore, this system is inconsistent, i.e., it has no solutions.

### Problem ( General Patterns for Systems of Linear Equations )

Find all values of a, b and c (or conditions on a, b and c) so that the system

$$\begin{array}{ccccccc} 2x & + & 3y & + & az & = & b \\ & & - & y & + & 2z & = & c \\ x & + & 3y & - & 2z & = & 1 \end{array}$$

has (i) a unique solution, (ii) no solutions, and (iii) infinitely many solutions. In (i) and (iii), find the solution(s).

### Problem ( General Patterns for Systems of Linear Equations )

Find all values of a, b and c (or conditions on a, b and c) so that the system

$$\begin{array}{rrrrrr} 2x & + & 3y & + & az & = & b \\ & & - & y & + & 2z & = & c \\ x & + & 3y & - & 2z & = & 1 \end{array}$$

has (i) a unique solution, (ii) no solutions, and (iii) infinitely many solutions. In (i) and (iii), find the solution(s).

### Solution

$$\left[ \begin{array}{ccc|c} 2 & 3 & a & b \\ 0 & -1 & 2 & c \\ 1 & 3 & -2 & 1 \end{array} \right]$$



### Problem ( General Patterns for Systems of Linear Equations )

Find all values of a, b and c (or conditions on a, b and c) so that the system

$$\begin{array}{rrrrrr} 2x & + & 3y & + & az & = & b \\ & & - & y & + & 2z & = & c \\ x & + & 3y & - & 2z & = & 1 \end{array}$$

has (i) a unique solution, (ii) no solutions, and (iii) infinitely many solutions. In (i) and (iii), find the solution(s).

### Solution

$$\left[ \begin{array}{ccc|c} 2 & 3 & a & b \\ 0 & -1 & 2 & c \\ 1 & 3 & -2 & 1 \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & -1 & 2 & c \\ 2 & 3 & a & b \end{array} \right]$$

Solution (continued)

$$\left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & -1 & 2 & c \\ 2 & 3 & a & b \end{array} \right]$$

Solution (continued)

$$\left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & -1 & 2 & c \\ 2 & 3 & a & b \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & -1 & 2 & c \\ 0 & -3 & a+4 & b-2 \end{array} \right]$$

Solution (continued)

$$\begin{aligned} & \left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & -1 & 2 & c \\ 2 & 3 & a & b \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & -1 & 2 & c \\ 0 & -3 & a+4 & b-2 \end{array} \right] \\ & \rightarrow \left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & 1 & -2 & -c \\ 0 & -3 & a+4 & b-2 \end{array} \right] \end{aligned}$$

Solution (continued)

$$\begin{aligned} & \left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & -1 & 2 & c \\ 2 & 3 & a & b \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & -1 & 2 & c \\ 0 & -3 & a+4 & b-2 \end{array} \right] \\ \rightarrow & \left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & 1 & -2 & -c \\ 0 & -3 & a+4 & b-2 \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 0 & 4 & 1+3c \\ 0 & 1 & -2 & -c \\ 0 & 0 & a-2 & b-2-3c \end{array} \right] \end{aligned}$$

Solution (continued)

$$\begin{aligned} & \left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & -1 & 2 & c \\ 2 & 3 & a & b \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & -1 & 2 & c \\ 0 & -3 & a+4 & b-2 \end{array} \right] \\ & \rightarrow \left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & 1 & -2 & -c \\ 0 & -3 & a+4 & b-2 \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 0 & 4 & 1+3c \\ 0 & 1 & -2 & -c \\ 0 & 0 & a-2 & b-2-3c \end{array} \right] \end{aligned}$$

Case 1.  $a - 2 \neq 0$ , i.e.,  $a \neq 2$ .

Solution (continued)

$$\begin{aligned} & \left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & -1 & 2 & c \\ 2 & 3 & a & b \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & -1 & 2 & c \\ 0 & -3 & a+4 & b-2 \end{array} \right] \\ & \rightarrow \left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & 1 & -2 & -c \\ 0 & -3 & a+4 & b-2 \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 0 & 4 & 1+3c \\ 0 & 1 & -2 & -c \\ 0 & 0 & a-2 & b-2-3c \end{array} \right] \end{aligned}$$

Case 1.  $a - 2 \neq 0$ , i.e.,  $a \neq 2$ . In this case,

$$\rightarrow \left[ \begin{array}{ccc|c} 1 & 0 & 4 & 1+3c \\ 0 & 1 & -2 & -c \\ 0 & 0 & 1 & \frac{b-2-3c}{a-2} \end{array} \right]$$

Solution (continued)

$$\begin{aligned} & \left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & -1 & 2 & c \\ 2 & 3 & a & b \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & -1 & 2 & c \\ 0 & -3 & a+4 & b-2 \end{array} \right] \\ & \rightarrow \left[ \begin{array}{ccc|c} 1 & 3 & -2 & 1 \\ 0 & 1 & -2 & -c \\ 0 & -3 & a+4 & b-2 \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 0 & 4 & 1+3c \\ 0 & 1 & -2 & -c \\ 0 & 0 & a-2 & b-2-3c \end{array} \right] \end{aligned}$$

Case 1.  $a - 2 \neq 0$ , i.e.,  $a \neq 2$ . In this case,

$$\rightarrow \left[ \begin{array}{ccc|c} 1 & 0 & 4 & 1+3c \\ 0 & 1 & -2 & -c \\ 0 & 0 & 1 & \frac{b-2-3c}{a-2} \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 0 & 0 & 1+3c-4\left(\frac{b-2-3c}{a-2}\right) \\ 0 & 1 & 0 & -c+2\left(\frac{b-2-3c}{a-2}\right) \\ 0 & 0 & 1 & \frac{b-2-3c}{a-2} \end{array} \right]$$



Solution (continued)

$$\left[ \begin{array}{ccc|c} 1 & 0 & 0 & 1 + 3c - 4\left(\frac{b-2-3c}{a-2}\right) \\ 0 & 1 & 0 & -c + 2\left(\frac{b-2-3c}{a-2}\right) \\ 0 & 0 & 1 & \frac{b-2-3c}{a-2} \end{array} \right]$$

Solution (continued)

$$\left[ \begin{array}{ccc|c} 1 & 0 & 0 & 1 + 3c - 4 \left( \frac{b-2-3c}{a-2} \right) \\ 0 & 1 & 0 & -c + 2 \left( \frac{b-2-3c}{a-2} \right) \\ 0 & 0 & 1 & \frac{b-2-3c}{a-2} \end{array} \right]$$

(i) When  $a \neq 2$ , the unique solution is

$$x = 1 + 3c - 4 \left( \frac{b-2-3c}{a-2} \right)$$

$$y = -c + 2 \left( \frac{b-2-3c}{a-2} \right)$$

$$z = \frac{b-2-3c}{a-2}$$

### Solution (continued)

Case 2. If  $a = 2$ , then the augmented matrix becomes

$$\left[ \begin{array}{ccc|c} 1 & 0 & 4 & 1 + 3c \\ 0 & 1 & -2 & -c \\ 0 & 0 & a - 2 & b - 2 - 3c \end{array} \right]$$

### Solution (continued)

Case 2. If  $a = 2$ , then the augmented matrix becomes

$$\left[ \begin{array}{ccc|c} 1 & 0 & 4 & 1+3c \\ 0 & 1 & -2 & -c \\ 0 & 0 & a-2 & b-2-3c \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 0 & 4 & 1+3c \\ 0 & 1 & -2 & -c \\ 0 & 0 & 0 & b-2-3c \end{array} \right]$$

From this we see that the system has no solutions when  $b - 2 - 3c \neq 0$ .

### Solution (continued)

Case 2. If  $a = 2$ , then the augmented matrix becomes

$$\left[ \begin{array}{ccc|c} 1 & 0 & 4 & 1+3c \\ 0 & 1 & -2 & -c \\ 0 & 0 & a-2 & b-2-3c \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 0 & 4 & 1+3c \\ 0 & 1 & -2 & -c \\ 0 & 0 & 0 & b-2-3c \end{array} \right]$$

From this we see that the system has no solutions when  $b - 2 - 3c \neq 0$ .

(ii) When  $a = 2$  and  $b - 3c \neq 2$ , the system has no solutions.

Solution (continued)

Finally when  $a = 2$  and  $b - 3c = 2$ , the augmented matrix becomes

Solution (continued)

Finally when  $a = 2$  and  $b - 3c = 2$ , the augmented matrix becomes

$$\left[ \begin{array}{ccc|c} 1 & 0 & 4 & 1 + 3c \\ 0 & 1 & -2 & -c \\ 0 & 0 & 0 & b - 2 - 3c \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 0 & 4 & 1 + 3c \\ 0 & 1 & -2 & -c \\ 0 & 0 & 0 & 0 \end{array} \right]$$

### Solution (continued)

Finally when  $a = 2$  and  $b - 3c = 2$ , the augmented matrix becomes

$$\left[ \begin{array}{ccc|c} 1 & 0 & 4 & 1 + 3c \\ 0 & 1 & -2 & -c \\ 0 & 0 & 0 & b - 2 - 3c \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 0 & 4 & 1 + 3c \\ 0 & 1 & -2 & -c \\ 0 & 0 & 0 & 0 \end{array} \right]$$

and the system has infinitely many solutions.



### Solution (continued)

Finally when  $a = 2$  and  $b - 3c = 2$ , the augmented matrix becomes

$$\left[ \begin{array}{ccc|c} 1 & 0 & 4 & 1+3c \\ 0 & 1 & -2 & -c \\ 0 & 0 & 0 & b-2-3c \end{array} \right] \rightarrow \left[ \begin{array}{ccc|c} 1 & 0 & 4 & 1+3c \\ 0 & 1 & -2 & -c \\ 0 & 0 & 0 & 0 \end{array} \right]$$

and the system has infinitely many solutions.

(iii) When  $a = 2$  and  $b - 3c = 2$ , the system has infinitely many solutions:

$$\left. \begin{array}{rcl} x & = & 1+3c - 4s \\ y & = & -c + 2s \\ z & = & s \end{array} \right\} \quad \text{for all } s \in \mathbb{R}.$$





# Rank

## Definition

The **rank** of a matrix  $A$ , denoted  $\text{rank } A$ , is the number of leading 1's in any row-echelon matrix obtained from  $A$  by performing elementary row operations.

Suppose  $A$  is the augmented matrix of a consistent system of  $m$  linear equations in  $n$  variables, and  $\text{rank } A = r$ .

$$\begin{array}{c} m \\ \left\{ \begin{array}{c} \left[ \begin{array}{cccc|c} * & * & * & * & * \\ * & * & * & * & * \\ * & * & * & * & * \\ * & * & * & * & * \\ * & * & * & * & * \end{array} \right] \end{array} \right. \end{array} \rightarrow \begin{array}{c} \left[ \begin{array}{cccc|c} \textcolor{red}{1} & * & * & * & * \\ 0 & 0 & \textcolor{red}{1} & * & * \\ 0 & 0 & 0 & \textcolor{red}{1} & * \\ 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \end{array} \right] \end{array}$$

$\underbrace{\hspace{10em}}_n$

$\underbrace{\hspace{10em}}_{r \text{ leading } 1\text{'s}}$

Suppose  $A$  is the augmented matrix of a consistent system of  $m$  linear equations in  $n$  variables, and  $\text{rank } A = r$ .

$$\begin{array}{c} m \\ \left\{ \begin{array}{c} \left[ \begin{array}{cccc|c} * & * & * & * & * \\ * & * & * & * & * \\ * & * & * & * & * \\ * & * & * & * & * \\ * & * & * & * & * \end{array} \right] \end{array} \right. \end{array} \rightarrow \begin{array}{c} \left[ \begin{array}{cccc|c} \textcolor{red}{1} & * & * & * & * \\ 0 & 0 & \textcolor{red}{1} & * & * \\ 0 & 0 & 0 & \textcolor{red}{1} & * \\ 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \end{array} \right] \end{array}$$

$\underbrace{\hspace{10em}}_n$

$\underbrace{\hspace{10em}}_{r \text{ leading } 1\text{'s}}$

Then the set of solutions to the system has  $n - r$  parameters, so

Suppose  $A$  is the augmented matrix of a consistent system of  $m$  linear equations in  $n$  variables, and  $\text{rank } A = r$ .

$$\begin{array}{c} m \\ \left\{ \begin{array}{c|c} \begin{matrix} * & * & * & * \\ * & * & * & * \\ * & * & * & * \\ * & * & * & * \\ * & * & * & * \end{matrix} & \begin{matrix} * \\ * \\ * \\ * \\ * \end{matrix} \end{array} \right. \end{array} \rightarrow \begin{array}{c} \begin{array}{c|c} \begin{matrix} \textcolor{red}{1} & * & * & * \\ 0 & 0 & \textcolor{red}{1} & * \\ 0 & 0 & 0 & \textcolor{red}{1} \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \end{matrix} & \begin{matrix} * \\ * \\ * \\ 0 \\ 0 \end{matrix} \end{array} \\ \underbrace{\hspace{10em}}_{n} \hspace{1em} \underbrace{\hspace{10em}}_{r \text{ leading } 1\text{'s}} \end{array}$$

Then the set of solutions to the system has  $n - r$  parameters, so

- if  $r < n$ , there is at least one parameter, and the system has infinitely many solutions;

Suppose  $A$  is the augmented matrix of a consistent system of  $m$  linear equations in  $n$  variables, and  $\text{rank } A = r$ .

$$\begin{array}{c} m \\ \left\{ \begin{array}{c|cccc} * & * & * & * & * \\ * & * & * & * & * \\ * & * & * & * & * \\ * & * & * & * & * \\ * & * & * & * & * \end{array} \right. \end{array} \rightarrow \begin{array}{c} \begin{array}{c|cccc} \textcolor{red}{1} & * & * & * & * \\ 0 & 0 & \textcolor{red}{1} & * & * \\ 0 & 0 & 0 & \textcolor{red}{1} & * \\ 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \end{array} \end{array}$$

$\underbrace{\hspace{10em}}_n$

$\underbrace{\hspace{10em}}_{r \text{ leading } 1\text{'s}}$

Then the set of solutions to the system has  $n - r$  parameters, so

- ▶ if  $r < n$ , there is at least one parameter, and the system has infinitely many solutions;
- ▶ if  $r = n$ , there are no parameters, and the system has a unique solution.







### Problem

Find the rank of  $A = \begin{bmatrix} a & b & 5 \\ 1 & -2 & 1 \end{bmatrix}$ .

### Solution

$$\begin{bmatrix} a & b & 5 \\ 1 & -2 & 1 \end{bmatrix} \rightarrow \begin{bmatrix} 1 & -2 & 1 \\ a & b & 5 \end{bmatrix} \rightarrow \begin{bmatrix} 1 & -2 & 1 \\ 0 & b+2a & 5-a \end{bmatrix}$$

If  $b+2a=0$  and  $5-a=0$ , i.e.,  $a=5$  and  $b=-10$ , then  $\text{rank } A = 1$ .  
Otherwise,  $\text{rank } A = 2$ .

For any system of linear equations, exactly one of the following holds:

For any system of linear equations, exactly one of the following holds:

1. the system is **inconsistent**;

For any system of linear equations, exactly one of the following holds:

1. the system is **inconsistent**;
2. the system has a **unique** solution, i.e., exactly one solution;

For any system of linear equations, exactly one of the following holds:

1. the system is **inconsistent**;
2. the system has a **unique** solution, i.e., exactly one solution;
3. the system has **infinitely many** solutions.

For any system of linear equations, exactly one of the following holds:

1. the system is **inconsistent**;
2. the system has a **unique** solution, i.e., exactly one solution;
3. the system has **infinitely many** solutions.

One can see what case applies by looking at the RREF matrix equivalent to the augmented matrix of the system and distinguishing three cases:

1. The last nonzero row is  $[0, \dots, 0, 1]$ : no solution.
2. The last nonzero row is **not**  $[0, \dots, 0, 1]$  and all variables are leading: unique solution.
3. The last nonzero row is **not**  $[0, \dots, 0, 1]$  and there are non-leading variables: infinitely many solutions.

## Problem

Solve the system

$$\begin{array}{rrrrrrrrrr} -3x_1 & + & 6x_2 & - & 4x_3 & - & 9x_4 & + & 3x_5 & = & -1 \\ -x_1 & + & 2x_2 & - & 2x_3 & - & 4x_4 & - & 3x_5 & = & 3 \\ x_1 & - & 2x_2 & + & 2x_3 & + & 2x_4 & - & 5x_5 & = & 1 \\ x_1 & - & 2x_2 & + & x_3 & + & 3x_4 & - & x_5 & = & 1 \end{array}$$



## Problem

Solve the system

$$\begin{array}{rrrrrrrrcl} -3x_1 & + & 6x_2 & - & 4x_3 & - & 9x_4 & + & 3x_5 & = & -1 \\ -x_1 & + & 2x_2 & - & 2x_3 & - & 4x_4 & - & 3x_5 & = & 3 \\ x_1 & - & 2x_2 & + & 2x_3 & + & 2x_4 & - & 5x_5 & = & 1 \\ x_1 & - & 2x_2 & + & x_3 & + & 3x_4 & - & x_5 & = & 1 \end{array}$$

## Solution

Begin by putting the augmented matrix in reduced row-echelon form.

$$\left[ \begin{array}{ccccc|c} 1 & -2 & 2 & 2 & -5 & 1 \\ -3 & 6 & -4 & -9 & 3 & -1 \\ -1 & 2 & -2 & -4 & -3 & 3 \\ 1 & -2 & 1 & 3 & -1 & 1 \end{array} \right]$$

## Problem

Solve the system

$$\begin{array}{rrrrrrrrcl} -3x_1 & + & 6x_2 & - & 4x_3 & - & 9x_4 & + & 3x_5 & = & -1 \\ -x_1 & + & 2x_2 & - & 2x_3 & - & 4x_4 & - & 3x_5 & = & 3 \\ x_1 & - & 2x_2 & + & 2x_3 & + & 2x_4 & - & 5x_5 & = & 1 \\ x_1 & - & 2x_2 & + & x_3 & + & 3x_4 & - & x_5 & = & 1 \end{array}$$

## Solution

Begin by putting the augmented matrix in reduced row-echelon form.

$$\left[ \begin{array}{ccccc|c} 1 & -2 & 2 & 2 & -5 & 1 \\ -3 & 6 & -4 & -9 & 3 & -1 \\ -1 & 2 & -2 & -4 & -3 & 3 \\ 1 & -2 & 1 & 3 & -1 & 1 \end{array} \right] \rightarrow \left[ \begin{array}{ccccc|c} 1 & -2 & 0 & 0 & -13 & 9 \\ 0 & 0 & 1 & 0 & 0 & -2 \\ 0 & 0 & 0 & 1 & 4 & -2 \\ 0 & 0 & 0 & 0 & 0 & 0 \end{array} \right]$$

## Problem

Solve the system

$$\begin{array}{rrrrrrrrcl} -3x_1 & + & 6x_2 & - & 4x_3 & - & 9x_4 & + & 3x_5 & = & -1 \\ -x_1 & + & 2x_2 & - & 2x_3 & - & 4x_4 & - & 3x_5 & = & 3 \\ x_1 & - & 2x_2 & + & 2x_3 & + & 2x_4 & - & 5x_5 & = & 1 \\ x_1 & - & 2x_2 & + & x_3 & + & 3x_4 & - & x_5 & = & 1 \end{array}$$

## Solution

Begin by putting the augmented matrix in reduced row-echelon form.

$$\left[ \begin{array}{ccccc|c} 1 & -2 & 2 & 2 & -5 & 1 \\ -3 & 6 & -4 & -9 & 3 & -1 \\ -1 & 2 & -2 & -4 & -3 & 3 \\ 1 & -2 & 1 & 3 & -1 & 1 \end{array} \right] \rightarrow \left[ \begin{array}{ccccc|c} 1 & -2 & 0 & 0 & -13 & 9 \\ 0 & 0 & 1 & 0 & 0 & -2 \\ 0 & 0 & 0 & 1 & 4 & -2 \\ 0 & 0 & 0 & 0 & 0 & 0 \end{array} \right]$$

The system is **consistent**.

## Problem

Solve the system

$$\begin{array}{rrrrrrrrcl} -3x_1 & + & 6x_2 & - & 4x_3 & - & 9x_4 & + & 3x_5 & = & -1 \\ -x_1 & + & 2x_2 & - & 2x_3 & - & 4x_4 & - & 3x_5 & = & 3 \\ x_1 & - & 2x_2 & + & 2x_3 & + & 2x_4 & - & 5x_5 & = & 1 \\ x_1 & - & 2x_2 & + & x_3 & + & 3x_4 & - & x_5 & = & 1 \end{array}$$

## Solution

Begin by putting the augmented matrix in reduced row-echelon form.

$$\left[ \begin{array}{ccccc|c} 1 & -2 & 2 & 2 & -5 & 1 \\ -3 & 6 & -4 & -9 & 3 & -1 \\ -1 & 2 & -2 & -4 & -3 & 3 \\ 1 & -2 & 1 & 3 & -1 & 1 \end{array} \right] \rightarrow \left[ \begin{array}{ccccc|c} 1 & -2 & 0 & 0 & -13 & 9 \\ 0 & 0 & 1 & 0 & 0 & -2 \\ 0 & 0 & 0 & 1 & 4 & -2 \\ 0 & 0 & 0 & 0 & 0 & 0 \end{array} \right]$$

The system is consistent. The rank of the augmented matrix is 3.

## Problem

Solve the system

$$\begin{array}{rrrrrrrrcl} -3x_1 & + & 6x_2 & - & 4x_3 & - & 9x_4 & + & 3x_5 & = & -1 \\ -x_1 & + & 2x_2 & - & 2x_3 & - & 4x_4 & - & 3x_5 & = & 3 \\ x_1 & - & 2x_2 & + & 2x_3 & + & 2x_4 & - & 5x_5 & = & 1 \\ x_1 & - & 2x_2 & + & x_3 & + & 3x_4 & - & x_5 & = & 1 \end{array}$$

## Solution

Begin by putting the augmented matrix in reduced row-echelon form.

$$\left[ \begin{array}{ccccc|c} 1 & -2 & 2 & 2 & -5 & 1 \\ -3 & 6 & -4 & -9 & 3 & -1 \\ -1 & 2 & -2 & -4 & -3 & 3 \\ 1 & -2 & 1 & 3 & -1 & 1 \end{array} \right] \rightarrow \left[ \begin{array}{ccccc|c} 1 & -2 & 0 & 0 & -13 & 9 \\ 0 & 0 & 1 & 0 & 0 & -2 \\ 0 & 0 & 0 & 1 & 4 & -2 \\ 0 & 0 & 0 & 0 & 0 & 0 \end{array} \right]$$

The system is consistent. The rank of the augmented matrix is 3.

Since the system is consistent, the set of solutions has  $5 - 3 = 2$  parameters.

### Solution (continued)

From the reduced row-echelon matrix

$$\left[ \begin{array}{ccccc|c} 1 & -2 & 0 & 0 & -13 & 9 \\ 0 & 0 & 1 & 0 & 0 & -2 \\ 0 & 0 & 0 & 1 & 4 & -2 \\ 0 & 0 & 0 & 0 & 0 & 0 \end{array} \right],$$

## Solution (continued)

From the reduced row-echelon matrix

$$\left[ \begin{array}{ccccc|c} 1 & -2 & 0 & 0 & -13 & 9 \\ 0 & 0 & 1 & 0 & 0 & -2 \\ 0 & 0 & 0 & 1 & 4 & -2 \\ 0 & 0 & 0 & 0 & 0 & 0 \end{array} \right],$$

we obtain the general solution

$$\left. \begin{array}{rcl} x_1 & = & 9 + 2r + 13s \\ x_2 & = & r \\ x_3 & = & -2 \\ x_4 & = & -2 - 4s \\ x_5 & = & s \end{array} \right\} \quad \forall r, s \in \mathbb{R}$$

### Solution (continued)

From the reduced row-echelon matrix

$$\left[ \begin{array}{ccccc|c} 1 & -2 & 0 & 0 & -13 & 9 \\ 0 & 0 & 1 & 0 & 0 & -2 \\ 0 & 0 & 0 & 1 & 4 & -2 \\ 0 & 0 & 0 & 0 & 0 & 0 \end{array} \right],$$

we obtain the general solution

$$\left. \begin{array}{rcl} x_1 & = & 9 + 2r + 13s \\ x_2 & = & r \\ x_3 & = & -2 \\ x_4 & = & -2 - 4s \\ x_5 & = & s \end{array} \right\} \quad \forall r, s \in \mathbb{R}$$

The solution has two parameters ( $r$  and  $s$ ) as we expected.



## Uniqueness of the Reduced Row-Echelon Form

# Uniqueness of the Reduced Row-Echelon Form

## Theorem

Systems of linear equations that correspond to row equivalent augmented matrices have exactly the same solutions.

# Uniqueness of the Reduced Row-Echelon Form

## Theorem

Systems of linear equations that correspond to row equivalent augmented matrices have exactly the same solutions.

## Theorem

Every matrix  $A$  is row equivalent to a **unique** reduced row-echelon matrix.

## Problem

Solve the system

$$2x + y + 3z = 1$$

$$2y - z + x = 0$$

$$9z + x - 4y = 2$$

## Problem

Solve the system

$$\begin{array}{rclclcl} 2x & + & y & + & 3z & = & 1 \\ 2y & - & z & + & x & = & 0 \\ 9z & + & x & - & 4y & = & 2 \end{array}$$

### Solution



### Solution (continued)

This row-echelon matrix corresponds to the system

$$\begin{aligned} x + 0y + \frac{7}{3}z &= -\frac{2}{3} \\ y - \frac{5}{3}z &= -\frac{1}{3} \end{aligned}$$

and thus

$$\begin{aligned}x &= \frac{2}{3} - \frac{7}{3}z \\ y &= -\frac{1}{3} + \frac{5}{3}z\end{aligned}$$

## Solution (continued)

This row-echelon matrix corresponds to the system

$$\begin{array}{rcrcrcrcrcl} x & + & 0y & + & \frac{7}{3}z & = & -\frac{2}{3} \\ & & y & - & \frac{5}{3}z & = & -\frac{1}{3} \end{array},$$

and thus

$$\begin{array}{rcrcrcrcl} x & = & \frac{2}{3} - \frac{7}{3}z \\ y & = & -\frac{1}{3} + \frac{5}{3}z \end{array}$$

Setting  $z = s$ , where  $s \in \mathbb{R}$ , gives us (as before):

$$\begin{array}{rcrcrcrcl} x & = & \frac{2}{3} - \frac{7}{3}s \\ y & = & -\frac{1}{3} + \frac{5}{3}s \\ z & = & s \end{array}$$



## Solution (continued)

This row-echelon matrix corresponds to the system

$$\begin{array}{rcrcrcrcrcl} x & + & 0y & + & \frac{7}{3}z & = & -\frac{2}{3} \\ & & y & - & \frac{5}{3}z & = & -\frac{1}{3} \end{array},$$

and thus

$$\begin{array}{rcrcrcrcrcl} x & = & \frac{2}{3} - \frac{7}{3}z \\ y & = & -\frac{1}{3} + \frac{5}{3}z \end{array}$$

Setting  $z = s$ , where  $s \in \mathbb{R}$ , gives us (as before):

$$\begin{array}{rcrcrcrcrcl} x & = & \frac{2}{3} - \frac{7}{3}s \\ y & = & -\frac{1}{3} + \frac{5}{3}s \\ z & = & s \end{array}$$

Always check your answer!







# One Application

## Problem

Derive the formula for  $1^r + 2^r + \cdots + n^r$  for  $r = 3$ .

## Solution

We know that  $1^3 + 2^3 + \cdots + n^3$  is a polynomial in  $n$  of order 4, namely,

$$1^3 + 2^3 + \cdots + n^3 = a_0 + a_1n + a_2n^2 + a_3n^3 + a_4n^4.$$

# One Application

## Problem

Derive the formula for  $1^r + 2^r + \cdots + n^r$  for  $r = 3$ .

## Solution

We know that  $1^3 + 2^3 + \cdots + n^3$  is a polynomial in  $n$  of order 4, namely,

$$1^3 + 2^3 + \cdots + n^3 = a_0 + a_1n + a_2n^2 + a_3n^3 + a_4n^4.$$

It is easy to see that when  $n = 0$ , both sides should be equal to zero. Hence,  $a_0 = 0$ .

# One Application

## Problem

Derive the formula for  $1^r + 2^r + \cdots + n^r$  for  $r = 3$ .

## Solution

We know that  $1^3 + 2^3 + \cdots + n^3$  is a polynomial in  $n$  of order 4, namely,

$$1^3 + 2^3 + \cdots + n^3 = a_0 + a_1n + a_2n^2 + a_3n^3 + a_4n^4.$$

It is easy to see that when  $n = 0$ , both sides should be equal to zero. Hence,  $a_0 = 0$ . Now we have 4 unknowns,  $a_1, \cdots, a_4$ . We can let  $n = 1, \cdots, 4$  to form 4 equations in order to find these unknowns:

$$\begin{array}{rcccccccl} 1^1a_1 & + & 1^2a_2 & + & 1^3a_3 & + & 1^4a_4 & = & 1^3 & (n = 1) \\ 2^1a_1 & + & 2^2a_2 & + & 2^3a_3 & + & 2^4a_4 & = & 1^3 + 2^3 & (n = 2) \\ 3^1a_1 & + & 3^2a_2 & + & 3^3a_3 & + & 3^4a_4 & = & 1^3 + 2^3 + 3^3 & (n = 3) \\ 4^1a_1 & + & 4^2a_2 & + & 4^3a_3 & + & 4^4a_4 & = & 1^3 + 2^3 + 3^3 + 4^3 & (n = 4) \end{array}$$

### Solution (continued)

Hence, we have the following augmented matrix:

$$\left( \begin{array}{cccc|c} 1 & 1 & 1 & 1 & 1 \\ 2 & 4 & 8 & 16 & 9 \\ 3 & 9 & 27 & 81 & 36 \\ 4 & 16 & 64 & 256 & 100 \end{array} \right)$$

### Solution (continued)

Hence, we have the following augmented matrix:

$$\left( \begin{array}{cccc|c} 1 & 1 & 1 & 1 & 1 \\ 2 & 4 & 8 & 16 & 9 \\ 3 & 9 & 27 & 81 & 36 \\ 4 & 16 & 64 & 256 & 100 \end{array} \right)$$

You can use Octave or Matlab to compute the reduced echelon form:

$$\left( \begin{array}{cccc|c} 1 & 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 & 1/4 \\ 0 & 0 & 1 & 0 & 1/2 \\ 0 & 0 & 0 & 1 & 1/4 \end{array} \right)$$



## Solution (continued)

Hence, we have the following augmented matrix:

$$\left( \begin{array}{cccc|c} 1 & 1 & 1 & 1 & 1 \\ 2 & 4 & 8 & 16 & 9 \\ 3 & 9 & 27 & 81 & 36 \\ 4 & 16 & 64 & 256 & 100 \end{array} \right)$$

You can use Octave or Matlab to compute the reduced echelon form:

$$\left( \begin{array}{cccc|c} 1 & 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 & 1/4 \\ 0 & 0 & 1 & 0 & 1/2 \\ 0 & 0 & 0 & 1 & 1/4 \end{array} \right)$$

Therefore, we have that

$$1^3 + 2^3 + \cdots + n^3 = \frac{n^2}{4} + \frac{n^3}{2} + \frac{n^4}{4} = \frac{1}{4}n^2(n+1)^2.$$

