

# Math 221: LINEAR ALGEBRA

## Chapter 2. Matrix Algebra

### §2-7. LU Factorization

Le Chen<sup>1</sup>

Emory University, 2021 Spring

(last updated on 02/08/2021)



Creative Commons License  
(CC BY-NC-SA)

<sup>1</sup>Slides are adapted from those by Karen Seyffarth from University of Calgary.

LU Factorization

Why do we need LU Factorization?

Finding the LU

Multiplier Method

LU-Algorithm

## LU Factorization

Why do we need LU Factorization?

Finding the LU

Multiplier Method

LU-Algorithm



# LU Factorization

## Definition

A matrix  $A = [a_{ij}]$  is called **upper triangular** if  $a_{ij} = 0$  whenever  $i > j$ . Thus the entries below the main diagonal equal 0.

# LU Factorization

## Definition

A matrix  $A = [a_{ij}]$  is called **upper triangular** if  $a_{ij} = 0$  whenever  $i > j$ . Thus the entries below the main diagonal equal 0.



# LU Factorization

## Definition

A matrix  $A = [a_{ij}]$  is called **upper triangular** if  $a_{ij} = 0$  whenever  $i > j$ . Thus the entries below the main diagonal equal 0.



A **lower triangular matrix** is defined similarly, as a matrix for which all entries above the main diagonal are equal to zero.

# LU Factorization

## Definition

A matrix  $A = [a_{ij}]$  is called **upper triangular** if  $a_{ij} = 0$  whenever  $i > j$ . Thus the entries below the main diagonal equal 0.



A **lower triangular matrix** is defined similarly, as a matrix for which all entries above the main diagonal are equal to zero.





An **LU factorization** of a matrix  $A$  is written

$$A = LU$$

where  $L$  is lower triangular matrix and  $U$  is upper triangular.

An **LU factorization** of a matrix  $A$  is written

$$A = LU$$

where  $L$  is lower triangular matrix and  $U$  is upper triangular.

We often require either  $L$  or  $U$  to have only 1's on the main diagonal.

An **LU factorization** of a matrix  $A$  is written

$$A = LU$$

where  $L$  is lower triangular matrix and  $U$  is upper triangular.

We often require either  $L$  or  $U$  to have only 1's on the main diagonal.

$$A = \begin{pmatrix} 1 & 0 & \cdots & 0 \\ * & 1 & & \vdots \\ \vdots & \ddots & \ddots & 0 \\ * & \cdots & * & 1 \end{pmatrix} \begin{pmatrix} * & * & \cdots & * \\ 0 & * & \ddots & \vdots \\ \vdots & \ddots & \ddots & * \\ 0 & \cdots & 0 & * \end{pmatrix}$$

LU Factorization

**Why do we need LU Factorization?**

Finding the LU

Multiplier Method

LU-Algorithm



## Why do we need LU Factorization?

The LU factorization often helps to quickly solve equations of the form  $A\vec{x} = \vec{b}$ .

## Why do we need LU Factorization?

The LU factorization often helps to quickly solve equations of the form  $A\vec{x} = \vec{b}$ .

Suppose we wish to find all solutions  $\vec{x}$  to the system  $A\vec{x} = B$ . The LU factorization of  $A$  can assist in this process.

## Why do we need LU Factorization?

The LU factorization often helps to quickly solve equations of the form  $A\vec{x} = \vec{b}$ .

Suppose we wish to find all solutions  $\vec{x}$  to the system  $A\vec{x} = B$ . The LU factorization of  $A$  can assist in this process.

Consider the following reduction:

$$\begin{aligned}A\vec{x} &= B \\(LU)\vec{x} &= B \\L(U\vec{x}) &= B \\L\vec{y} &= B\end{aligned}$$



## Why do we need LU Factorization?

The LU factorization often helps to quickly solve equations of the form  $A\vec{x} = \vec{b}$ .

Suppose we wish to find all solutions  $\vec{x}$  to the system  $A\vec{x} = B$ . The LU factorization of  $A$  can assist in this process.

Consider the following reduction:

$$\begin{aligned}A\vec{x} &= B \\(LU)\vec{x} &= B \\L(U\vec{x}) &= B \\L\vec{y} &= B\end{aligned}$$

Therefore, if we can solve  $L\vec{y} = B$  for  $\vec{y}$ , then all that remains is to solve  $U\vec{x} = \vec{y}$  for  $\vec{x}$ .

## Example

Find all solutions to

$$\begin{bmatrix} 1 & 3 & 2 & 0 \\ 3 & 10 & 5 & 1 \\ 0 & -1 & 2 & 1 \end{bmatrix} \begin{bmatrix} x_1 \\ x_2 \\ x_3 \\ x_4 \end{bmatrix} = \begin{bmatrix} 2 \\ 4 \\ 6 \end{bmatrix}$$

## Example

Find all solutions to

$$\begin{bmatrix} 1 & 3 & 2 & 0 \\ 3 & 10 & 5 & 1 \\ 0 & -1 & 2 & 1 \end{bmatrix} \begin{bmatrix} x_1 \\ x_2 \\ x_3 \\ x_4 \end{bmatrix} = \begin{bmatrix} 2 \\ 4 \\ 6 \end{bmatrix}$$

## Solution

Using a method of your choice, verify that the LU factorization of A gives

$$L = \begin{bmatrix} 1 & 0 & 0 \\ 3 & 1 & 0 \\ 0 & -1 & 1 \end{bmatrix}, U = \begin{bmatrix} 1 & 3 & 2 & 0 \\ 0 & 1 & -1 & 1 \\ 0 & 0 & 1 & 2 \end{bmatrix}$$

Solution (continued)

Let  $\vec{y} = \begin{bmatrix} y_1 \\ y_2 \\ y_3 \end{bmatrix}$  and solve  $L\vec{y} = \vec{b}$ .

Solution (continued)

Let  $\vec{y} = \begin{bmatrix} y_1 \\ y_2 \\ y_3 \end{bmatrix}$  and solve  $L\vec{y} = \vec{b}$ .

$$\begin{bmatrix} 1 & 0 & 0 \\ 3 & 1 & 0 \\ 0 & -1 & 1 \end{bmatrix} \begin{bmatrix} y_1 \\ y_2 \\ y_3 \end{bmatrix} = \begin{bmatrix} 2 \\ 4 \\ 6 \end{bmatrix}$$

Solution (continued)

Let  $\vec{y} = \begin{bmatrix} y_1 \\ y_2 \\ y_3 \end{bmatrix}$  and solve  $L\vec{y} = \vec{b}$ .

$$\begin{bmatrix} 1 & 0 & 0 \\ 3 & 1 & 0 \\ 0 & -1 & 1 \end{bmatrix} \begin{bmatrix} y_1 \\ y_2 \\ y_3 \end{bmatrix} = \begin{bmatrix} 2 \\ 4 \\ 6 \end{bmatrix}$$

The solution is  $\vec{y} = \begin{bmatrix} 2 \\ -2 \\ 4 \end{bmatrix}$ .

Solution (continued)

Let  $\vec{y} = \begin{bmatrix} y_1 \\ y_2 \\ y_3 \end{bmatrix}$  and solve  $L\vec{y} = \vec{b}$ .

$$\begin{bmatrix} 1 & 0 & 0 \\ 3 & 1 & 0 \\ 0 & -1 & 1 \end{bmatrix} \begin{bmatrix} y_1 \\ y_2 \\ y_3 \end{bmatrix} = \begin{bmatrix} 2 \\ 4 \\ 6 \end{bmatrix}$$

The solution is  $\vec{y} = \begin{bmatrix} 2 \\ -2 \\ 4 \end{bmatrix}$ .

Now we solve  $U\vec{x} = \vec{y}$ .

$$\begin{bmatrix} 1 & 3 & 2 & 0 \\ 0 & 1 & -1 & 1 \\ 0 & 0 & 1 & 2 \end{bmatrix} \begin{bmatrix} x_1 \\ x_2 \\ x_3 \\ x_4 \end{bmatrix} = \begin{bmatrix} 2 \\ -2 \\ 4 \end{bmatrix}$$

## Solution (continued)

Multiplying and solving (or finding the reduced row-echelon form ), the general solution is given by

$$\vec{x} = \begin{bmatrix} -12 \\ 2 \\ 4 \\ 0 \end{bmatrix} + \begin{bmatrix} 13 \\ -3 \\ -2 \\ 1 \end{bmatrix} t, \quad \forall t \in \mathbb{R}.$$





LU Factorization

Why do we need LU Factorization?

**Finding the LU**

Multiplier Method

LU-Algorithm



## Finding the LU Factorization

**Condition for the existence of LU factorization:** A matrix  $A$  has LU factorization provided that  $A$  can be **lower reduced**, namely, the row-echelon form of  $A$  can be calculated without interchanging rows.

## Finding the LU Factorization

**Condition for the existence of LU factorization:** A matrix A has LU factorization provided that A can be **lower reduced**, namely, the row-echelon form of A can be calculated without interchanging rows.

### Example

Determine if the LU factorization of A exists, and if so, find it.

$$A = \begin{bmatrix} 1 & 1 & 2 \\ 2 & 3 & 0 \\ 1 & 0 & 5 \end{bmatrix}$$

## Finding the LU Factorization

**Condition for the existence of LU factorization:** A matrix A has LU factorization provided that A can be **lower reduced**, namely, the row-echelon form of A can be calculated without interchanging rows.

### Example

Determine if the LU factorization of A exists, and if so, find it.

$$A = \begin{bmatrix} 1 & 1 & 2 \\ 2 & 3 & 0 \\ 1 & 0 & 5 \end{bmatrix}$$

### Solution

Because the row-echelon form can be obtained without interchanging rows:

## Finding the LU Factorization

**Condition for the existence of LU factorization:** A matrix A has LU factorization provided that A can be **lower reduced**, namely, the row-echelon form of A can be calculated without interchanging rows.

### Example

Determine if the LU factorization of A exists, and if so, find it.

$$A = \begin{bmatrix} 1 & 1 & 2 \\ 2 & 3 & 0 \\ 1 & 0 & 5 \end{bmatrix}$$

### Solution

Because the row-echelon form can be obtained without interchanging rows:

$$\begin{bmatrix} 1 & 1 & 2 \\ 2 & 3 & 0 \\ 1 & 0 & 5 \end{bmatrix} \xrightarrow{r_2 - 2r_1} \begin{bmatrix} 1 & 1 & 2 \\ 0 & 1 & -4 \\ 1 & 0 & 5 \end{bmatrix} \xrightarrow{r_3 - r_1} \begin{bmatrix} 1 & 1 & 2 \\ 0 & 1 & -4 \\ 0 & -1 & 3 \end{bmatrix} \xrightarrow{r_3 + r_2} \begin{bmatrix} 1 & 1 & 2 \\ 0 & 1 & -4 \\ 0 & 0 & -1 \end{bmatrix}$$

the LU factorization exists, or A can be lower reduced.

## Solution (continued)

We proceed to finding L and U. Assign variables to the unknown entries and multiply.

$$\begin{aligned} A &= \begin{bmatrix} 1 & 1 & 2 \\ 2 & 3 & 0 \\ 1 & 0 & 5 \end{bmatrix} = \begin{bmatrix} 1 & 0 & 0 \\ x & 1 & 0 \\ y & z & 1 \end{bmatrix} \begin{bmatrix} a & d & e \\ 0 & b & f \\ 0 & 0 & c \end{bmatrix} \\ &= \begin{bmatrix} a & d & e \\ ax & dx + b & ex + f \\ ay & dy + bz & ey + fz + c \end{bmatrix} \end{aligned}$$

## Solution (continued)

We proceed to finding L and U. Assign variables to the unknown entries and multiply.

$$\begin{aligned} A = \begin{bmatrix} 1 & 1 & 2 \\ 2 & 3 & 0 \\ 1 & 0 & 5 \end{bmatrix} &= \begin{bmatrix} 1 & 0 & 0 \\ x & 1 & 0 \\ y & z & 1 \end{bmatrix} \begin{bmatrix} a & d & e \\ 0 & b & f \\ 0 & 0 & c \end{bmatrix} \\ &= \begin{bmatrix} a & d & e \\ ax & dx + b & ex + f \\ ay & dy + bz & ey + fz + c \end{bmatrix} \end{aligned}$$

Solving each entry will give us values for the unknown entries.



Solution (continued)

$$\begin{bmatrix} 1 & 1 & 2 \\ 2 & 3 & 0 \\ 1 & 0 & 5 \end{bmatrix} = \begin{bmatrix} a & d & e \\ ax & dx + b & ex + f \\ ay & dy + bz & ey + fz + c \end{bmatrix}$$

## Solution (continued)

$$\begin{bmatrix} 1 & 1 & 2 \\ 2 & 3 & 0 \\ 1 & 0 & 5 \end{bmatrix} = \begin{bmatrix} a & d & e \\ ax & dx + b & ex + f \\ ay & dy + bz & ey + fz + c \end{bmatrix}$$

We see easily that  $a = 1$ ,  $d = 1$ , and  $e = 2$ . Continuing to solve the first column gives  $x = 2$ ,  $y = 1$ . The other values are calculated as follows.

## Solution (continued)

$$\begin{bmatrix} 1 & 1 & 2 \\ 2 & 3 & 0 \\ 1 & 0 & 5 \end{bmatrix} = \begin{bmatrix} a & d & e \\ ax & dx + b & ex + f \\ ay & dy + bz & ey + fz + c \end{bmatrix}$$

We see easily that  $a = 1$ ,  $d = 1$ , and  $e = 2$ . Continuing to solve the first column gives  $x = 2$ ,  $y = 1$ . The other values are calculated as follows.

$$\begin{array}{rcl} dx + b & = & 3 \\ (1)(2) + b & = & 3 \\ b & = & 1 \end{array} \qquad \begin{array}{rcl} ex + f & = & 0 \\ (2)(2) + f & = & 0 \\ f & = & -4 \end{array}$$

$$\begin{array}{rcl} dy + bz & = & 0 \\ (1)(1) + (1)z & = & 0 \\ z & = & -1 \end{array} \qquad \begin{array}{rcl} ey + fz + c & = & 5 \\ (2)(1) + (-4)(-1) + c & = & 5 \\ c & = & -1 \end{array}$$



## Solution (continued)

Therefore,

$$\begin{array}{c} L \\ \| \\ \begin{bmatrix} 1 & 0 & 0 \\ x & 1 & 0 \\ y & z & 1 \end{bmatrix} \\ \| \\ \begin{bmatrix} 1 & 0 & 0 \\ 2 & 1 & 0 \\ 1 & -1 & 1 \end{bmatrix} \end{array}$$

$$\begin{array}{c} U \\ \| \\ \begin{bmatrix} a & d & e \\ 0 & b & f \\ 0 & 0 & c \end{bmatrix} \\ \| \\ \begin{bmatrix} 1 & 1 & 2 \\ 0 & 1 & -4 \\ 0 & 0 & -1 \end{bmatrix} \end{array}$$



## Remark

If you want the diagonal terms of  $U$  to be all 1's:

$$\begin{bmatrix} 1 & 0 & 0 \\ 2 & 1 & 0 \\ 1 & -1 & 1 \end{bmatrix} \begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & -1 \end{bmatrix} \begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & -1 \end{bmatrix} \begin{bmatrix} 1 & 1 & 2 \\ 0 & 1 & -4 \\ 0 & 0 & -1 \end{bmatrix}$$

||

$$\underbrace{\begin{bmatrix} 1 & 0 & -0 \\ 2 & 1 & -0 \\ 1 & -1 & -1 \end{bmatrix}}_L \quad \underbrace{\begin{bmatrix} 1 & 1 & 2 \\ 0 & 1 & -4 \\ -0 & -0 & 1 \end{bmatrix}}_U$$



LU Factorization

Why do we need LU Factorization?

Finding the LU

**Multiplier Method**

LU-Algorithm





## Multiplier Method

The following process for finding  $L$  and  $U$ , called the **multiplier method**, can be more efficient.

## Multiplier Method

The following process for finding L and U, called the **multiplier method**, can be more efficient.

### Example

Find the LU factorization of  $A = \begin{bmatrix} 1 & 1 & 2 \\ 2 & 3 & 0 \\ 1 & 0 & 5 \end{bmatrix}$

## Multiplier Method

The following process for finding L and U, called the **multiplier method**, can be more efficient.

### Example

Find the LU factorization of  $A = \begin{bmatrix} 1 & 1 & 2 \\ 2 & 3 & 0 \\ 1 & 0 & 5 \end{bmatrix}$

### Solution

First, write A as

$$\begin{bmatrix} 1 & 1 & 2 \\ 2 & 3 & 0 \\ 1 & 0 & 5 \end{bmatrix}$$

||

$$\begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} 1 & 1 & 2 \\ 2 & 3 & 0 \\ 1 & 0 & 5 \end{bmatrix}$$

## Multiplier Method

The following process for finding L and U, called the **multiplier method**, can be more efficient.

### Example

Find the LU factorization of  $A = \begin{bmatrix} 1 & 1 & 2 \\ 2 & 3 & 0 \\ 1 & 0 & 5 \end{bmatrix}$

### Solution

First, write A as

$$\begin{bmatrix} 1 & 1 & 2 \\ 2 & 3 & 0 \\ 1 & 0 & 5 \end{bmatrix}$$

||

$$\begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} 1 & 1 & 2 \\ 2 & 3 & 0 \\ 1 & 0 & 5 \end{bmatrix}$$

## Solution (continued)

To do so, we use row operations to remove the entries of  $A$  below the main diagonal. For every operation we apply to  $A$  (the matrix on the right), we apply the inverse operation to the identity matrix (on the left). This ensures the product remains the same.

## Solution (continued)

To do so, we use row operations to remove the entries of  $A$  below the main diagonal. For every operation we apply to  $A$  (the matrix on the right), we apply the inverse operation to the identity matrix (on the left). This ensures the product remains the same.

The first step is to add  $(-2)$  times the first row of  $A$  to the second row. To preserve the product, add  $(2)$  times the second column to the first column, for the matrix on the left.

||

$$\begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} 1 & 0 & 0 \\ 2 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} 1 & 0 & 0 \\ -2 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} 1 & 1 & 2 \\ 2 & 3 & 0 \\ 1 & 0 & 5 \end{bmatrix}$$

||

$$c_1 + 2c_2 \rightarrow c_1 \begin{bmatrix} 1 & 0 & 0 \\ 2 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} 1 & 1 & 2 \\ 0 & 1 & -4 \\ 1 & 0 & 5 \end{bmatrix} r_2 - 2r_1 \rightarrow r_2$$



## Solution (continued)

We proceed in the same way.

$$c_1 + c_3 \rightarrow c_1 \quad \begin{bmatrix} 1 & 0 & 0 \\ 2 & 1 & 0 \\ 1 & 0 & 1 \end{bmatrix} \quad \begin{bmatrix} 1 & 1 & 2 \\ 0 & 1 & -4 \\ 0 & -1 & 3 \end{bmatrix} \quad r_3 - r_1 \rightarrow r_3$$

$$c_2 - c_3 \rightarrow c_2 \quad \begin{bmatrix} 1 & 0 & 0 \\ 2 & 1 & 0 \\ 1 & -1 & 1 \end{bmatrix} \quad \begin{bmatrix} 1 & 1 & 2 \\ 0 & 1 & -4 \\ 0 & 0 & -1 \end{bmatrix} \quad r_3 + r_2 \rightarrow r_3$$



## Solution (continued)

We proceed in the same way.

$$c_1 + c_3 \rightarrow c_1 \quad \begin{bmatrix} 1 & 0 & 0 \\ 2 & 1 & 0 \\ 1 & 0 & 1 \end{bmatrix} \quad \begin{bmatrix} 1 & 1 & 2 \\ 0 & 1 & -4 \\ 0 & -1 & 3 \end{bmatrix} \quad r_3 - r_1 \rightarrow r_3$$

$$c_2 - c_3 \rightarrow c_2 \quad \begin{bmatrix} 1 & 0 & 0 \\ 2 & 1 & 0 \\ 1 & -1 & 1 \end{bmatrix} \quad \begin{bmatrix} 1 & 1 & 2 \\ 0 & 1 & -4 \\ 0 & 0 & -1 \end{bmatrix} \quad r_3 + r_2 \rightarrow r_3$$

At this point we have a lower triangular matrix  $L$  on the left, and an upper triangular matrix  $U$  on the right so we are done. You can (and should!) check that this product equals  $A$ .

If you want the diagonal terms of  $U$  to be all 1's:

$$-1 \times c_3 \rightarrow c_3 \quad \begin{bmatrix} 1 & 0 & 0 \\ 2 & 1 & 0 \\ 1 & -1 & -1 \end{bmatrix} \quad \begin{bmatrix} 1 & 1 & 2 \\ 0 & 1 & -4 \\ 0 & 0 & 1 \end{bmatrix} \quad -1 \times r_3 \rightarrow r_3$$



## Problem

Use the multiplier method to verify the LU factorization for

$$A = \begin{bmatrix} 1 & 4 & 2 \\ 3 & 13 & 5 \\ -2 & -7 & -4 \end{bmatrix}$$

## Problem

Use the multiplier method to verify the LU factorization for

$$A = \begin{bmatrix} 1 & 4 & 2 \\ 3 & 13 & 5 \\ -2 & -7 & -4 \end{bmatrix}$$

## Solution

$$A = \begin{bmatrix} 1 & 4 & 2 \\ 3 & 13 & 5 \\ -2 & -7 & -4 \end{bmatrix} = \begin{bmatrix} 1 & 0 & 0 \\ 3 & 1 & 0 \\ -2 & 1 & 1 \end{bmatrix} \begin{bmatrix} 1 & 4 & 2 \\ 0 & 1 & -1 \\ 0 & 0 & 1 \end{bmatrix} = LU$$



LU Factorization

Why do we need LU Factorization?

Finding the LU

Multiplier Method

**LU-Algorithm**

## Theorem ( LU-Algorithm )

Let  $A$  be an  $m \times n$  matrix of rank  $r$ , and suppose that  $A$  can be lower reduced to a row-echelon matrix  $U$ . Then  $A = LU$  where the lower triangular, invertible matrix  $L$  is constructed as follows:

1. If  $A = 0$ , take  $L = I_m$  and  $U = 0$ .
2. If  $A \neq 0$ , write  $A_1 = A$  and let  $\vec{c}_1$  be the **leading column** of  $A_1$ . Use  $\vec{c}_1$  to create the first leading 1 and make its below all zeros. When this is completed, let  $A_2$  denote the matrix consisting of rows 2 to  $m$  of the matrix just created.
3. If  $A_2 \neq 0$ , let  $\vec{c}_2$  be the leading column of  $A_2$  and repeat Step 2 on  $A_2$  to create  $A_3$ .
4. Continue in this way until  $U$  is reached, where all rows below the last leading 1 consist of zeros. This will happen after  $r$  steps.
5. Create  $L$  by placing  $\vec{c}_1, \vec{c}_2, \dots, \vec{c}_r$  at the bottom of the first  $r$  columns of  $I_m$ .

## Problem

Find an LU-factorization for  $A = \begin{bmatrix} 2 & 4 & 2 \\ 1 & 1 & 2 \\ -1 & 0 & 2 \end{bmatrix}$ .

## Solution

$$\begin{bmatrix} 2 & 4 & 2 \\ 1 & 1 & 2 \\ -1 & 0 & 2 \end{bmatrix} \rightarrow \begin{bmatrix} 1 & 2 & 1 \\ 0 & -1 & 1 \\ 0 & 2 & 3 \end{bmatrix} \rightarrow \begin{bmatrix} 1 & 2 & 1 \\ 0 & 1 & -1 \\ 0 & 0 & 5 \end{bmatrix} \rightarrow \begin{bmatrix} 1 & 2 & 1 \\ 0 & 1 & -1 \\ 0 & 0 & 1 \end{bmatrix} = U$$

## Problem

Find an LU-factorization for  $A = \begin{bmatrix} 2 & 4 & 2 \\ 1 & 1 & 2 \\ -1 & 0 & 2 \end{bmatrix}$ .

## Solution

$$\begin{bmatrix} 2 & 4 & 2 \\ 1 & 1 & 2 \\ -1 & 0 & 2 \end{bmatrix} \rightarrow \begin{bmatrix} 1 & 2 & 1 \\ 0 & -1 & 1 \\ 0 & 2 & 3 \end{bmatrix} \rightarrow \begin{bmatrix} 1 & 2 & 1 \\ 0 & 1 & -1 \\ 0 & 0 & 5 \end{bmatrix} \rightarrow \begin{bmatrix} 1 & 2 & 1 \\ 0 & 1 & -1 \\ 0 & 0 & 1 \end{bmatrix} = U$$

$$\begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix} \rightarrow \begin{bmatrix} 2 & 0 & 0 \\ 1 & 1 & 0 \\ -1 & 0 & 1 \end{bmatrix} \rightarrow \begin{bmatrix} 2 & 0 & 0 \\ 1 & -1 & 0 \\ -1 & 2 & 1 \end{bmatrix} \rightarrow \begin{bmatrix} 2 & 0 & 0 \\ 1 & -1 & 0 \\ -1 & 2 & 5 \end{bmatrix} = L$$









## Solution

$$\begin{bmatrix} 5 & -5 & 10 & 0 & 5 \\ -3 & 3 & 2 & 2 & 1 \\ -2 & 2 & 0 & -1 & 0 \\ 1 & -1 & 10 & 2 & 5 \end{bmatrix}$$

↓

$$\begin{bmatrix} 1 & -1 & 2 & 0 & 1 \\ 0 & 0 & 8 & 2 & 4 \\ 0 & 0 & 4 & -1 & 2 \\ 0 & 0 & 8 & 2 & 4 \end{bmatrix}$$

↓

$$\begin{bmatrix} 1 & -1 & 2 & 0 & 1 \\ 0 & 0 & 1 & 1/4 & 1/2 \\ 0 & 0 & 0 & -2 & 0 \\ 0 & 0 & 0 & 0 & 0 \end{bmatrix}$$

↓

$$\begin{bmatrix} 1 & -1 & 2 & 0 & 1 \\ 0 & 0 & 1 & 1/4 & 1/2 \\ 0 & 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 0 & 0 \end{bmatrix}$$

||  
U

⇓

L  
||

$$\begin{bmatrix} 5 & 0 & 0 & 0 \\ -3 & 8 & 0 & 0 \\ -2 & 4 & -2 & 0 \\ 1 & 8 & 0 & 1 \end{bmatrix}$$

